

MULTISPORT Range PRO Readability 110 m

BASKET BALL - HANDBALL - VOLLEYBALL - TENNIS - TABLE TENNIS - BADMINTON - FUTSAL - RINK HOCKEY
IN LINE HOCKEY - ICE HOCKEY - UNIHOCKEY / FLOORBALL - NETBALL - BOXING - FREE MODE

452 MB 3123-123

Player	Points	Reb	Ass	Stk	FT	3Pt	Blk	Stl	Team
PARKER	28	...	1						FRANCE
PIETRUS	13	*	10						FRANCE
GELABALE	37	...	4						FRANCE
WEIS	45	...	23						FRANCE
FAUTHOUX	15	**	2						FRANCE
RIGAudeau	8	**	15						FRANCE
JULIAN	59	*	7						FRANCE
DIARRA	34	...	19						FRANCE
SCHMITT	20	...	6						FRANCE
DIAW	47	...	24						FRANCE
BARBERISTO	62	**	18						FRANCE
GIFFA	96	...	3						FRANCE
CALABRIA	28	...	1						ITALIE
BASILE	13	*	10						ITALIE
GALANDA	37	...	4						ITALIE
SORAGNA	45	...	23						ITALIE
MARCONATO	15	**	2						ITALIE
POZZECCO	8	**	15						ITALIE
RIGHETTI	59	*	7						ITALIE
MANCINELLI	34	...	19						ITALIE
BULERRI	20	...	6						ITALIE
MORDANTE	47	...	24						ITALIE
CHIACIG	62	**	18						ITALIE
GIGLI	96	...	3						ITALIE

(non contractual picture)



Composition

- 1 scoreboard made of 6 modules
- 2 control consoles, 1 start/stop timer console
- 1 PC keyboard
- 2 carrying cases for control consoles
- 3 mains cables
- Junction box and transmission cables (for cable controlled version)
- Operating and installation instructions

Description

Use:	Indoor
Transmission:	Cable. Radio transmission (868 MHz) as an option.
Readability:	110m, angle >160°
Dimensions:	5300 x 2000 x 90mm
Weight:	170 kg
Power supply:	230V / 50-60Hz
Power consumed:	610 VA
Protection:	Unbreakable matt polycarbonate front face (DIN 18032-3)
Horn:	1x internal horn, 116dB at 1m
Mains cable (supplied):	3x20 m – Type: 230V, 3G, 0.75 mm ²
Cable controlled:	For cable controlled models or radio controlled models with cable set: Junction Box + 50 m transmission cable (scoreboard/junction box) – Type: phone cable 2 pairs 6/10th + 10 m transmission cable DIN/DIN (junction box/console)

Display functions

Score:	2 x 3 red LED digits (25 cm)
Period:	1 green LED digit (20 cm)
Team names:	20 yellow LED alphanumeric characters (12 cm)
Moving messages (Ads/Sponsor):	1000 characters
Ball possession:	2 red LED arrows
Timer/Rest period:	4 white LED digits (25 cm) + blinking points
Team fouls (BB) or sets (VB, T, TT...):	2 yellow LED digits (20 cm)
Time out (BB, HB, VB) /No. of exclusions (HB):	2 x 3 green LED points
Excluded player (HB)/ last penalized player (BB) / set result for home team (VB, T, TT...):	6 x 2 yellow LED digits (16 cm)
Penalty timer (HB) / Time-out timer (BB) / No. of individual fouls for last penalized player (BB)	6 x 3 red LED digits (16 cm) + blinking points
Set result for guest team (VB, T, TT...):	10 yellow LED alphanumeric characters (9 cm) per player (12)
Player names (2 modules):	2 yellow LED digits (9 cm) per player (12)
Individual fouls (BB) (2 modules):	5 yellow LED points + 1 red LED point per player (12)
Individual points (2 modules):	2 red LED digits (9 cm) per player (12)
Day Time:	When the scoreboard is not in use

Control consoles

- 2 consoles:** (340 x 175 x 60 mm) with LCD screen with 2 lanes of 20 characters (9mm high)
 - **Main console:** management of the main functions
 - Control console for **individual fouls and points**
- 1 Start/stop timer console:** 145 x 150 x 40 mm for timer, time out, horn
- 1 Keyboard** Entering team and players names + moving messages (option)
- 1 charger (radio):** Hold the consoles in charge when there are not in use. (Autonomy max 16 h)
- Connection plugs:** DIN between the consoles
- USB Port:** For program update or connect PC keyboard
- Programme:** 14 sport disciplines + « Free mode » to create your own sport discipline or for additional sports (wrestling, Pelota...)

Multilingual Programme

Options

TV Interface (RS 485):	Data transmission for TV broadcasting
Sound Interface:	Connection with sport hall sound system - Horn sound amplifier
DCF or GPS Antenna:	For accurate time synchronisation
Cable set:	Cable mode for radio controlled scoreboard
Precision Time Interface:	Connection with electronic whistle
Pair of shot-clocks:	Attack timer with or without main time repeater
Led Strips:	Electric light to be installed behind the backboard
MPA:	Ball possession indicator